

913 MULTISWITCHES

9X16 FINAL MULTISWITCH, EU PSU



Code : **9130306**

Model : **MB-0916**

Description

Cascadable multiswitches for 8 polarities and terrestrial TV with 16 outputs. The outputs are amplified in the satellite IF band. Need to be powered from each individual receiver so that the switching and amplification of each derived output will function.

Applications

Medium-sized collective satellite and terrestrial TV installations. It is essential that they be mounted along with end multiswitches, so as to obtain distributions of up to 64 outlets on a single line if they are installed with intermediary amplifiers.

Characteristics

Shielded metal chassis with plastic supports. F-type connectors. Earthed.

CÓDIGO-CODE-CODE		9130304		9130305		9130306	
MODELO-MODEL-MODELE		MB-0908		MB-0912		MB-0916	
Entradas/salidas/derivaciones Inputs/outputs/taps Giriş/çıkış/yan çıkış Entrées/sorties/dérivations		9/0/8		9/0/12		9/0/16	
Rango de frecuencia Frequency range Frekans Gamme de fréquences	Band	TV	SAT	TV	SAT	TV	SAT
	MHz	47-862	950-2150	47-862	950-2150	47-862	950-2150
Atenuación de derivación Tap loss Yan çıkış kaybı Atténuation de dérivation		dB ±TOL	0 ±3,0	0 ±3,0	0 ±3,0	1 ±3,0	1 ±3,0
Nivel de salida Output level Çıkış seviyesi Niveau de sortie		dB μ V (DIN 45004B)	99 100 (IMD ₃ -35 dB) 95 (IMD ₂ -35 dB)	96 (DIN 45004B)	96 100 (IMD ₃ -35 dB) 92 (IMD ₂ -35 dB)	96 (DIN 45004B)	96 100 (IMD ₃ -35 dB) 92 (IMD ₂ -35 dB)
Rechazo entre bandas Rejection between bands Girişler arası izolasyon Rejection entre bandes		dB	>25 TV/SAT >65 SAT/TV				
Desacoplo entre usuarios Isolation between users Yan çıkışlar arası izolasyon Découplage entre utilisateurs		dB	>25 TV >30 SAT				
Desacoplo de conmutación Isolation of switching Anatharma Découplage de commutation		dB	>30 SAT/SAT				
Conmutación de las salidas Switching the outputs Uydu seçimi Commutation des sorties			DiSEqC 2.0 13V= /18V= 0/22 KHz				
Alimentación de las LNB Power supply of the LNB LNB beslemesi Alimentation des LNB			2000mA / 16V=				
Consumo desde el receptor Consumption from the receiver Uydu alıcısından çekilen akım Consumation du récepteur		mA	42 ±2 (13/18V=)				

IMD₃-35 dB: 3 unequal carriers, EN 60728-5

IMD₂-35 dB: 2 equal carriers, EN 60728-5

Data published in compliance with the definitions and measurement methods of the following standards: EN 60728-3, EN-60728-4 and EN 60728-5

